



F&F Filipowski sp. j  
ul. Konstantynowska 79/81  
95-200 Pabianice POLAND  
tel/fax 48 42 2270971  
e-mail: fif@fif.com.pl

## ASO-202

**STAIRCASE TIMERS**  
with additional function of counter blockade



[www.fif.com.pl](http://www.fif.com.pl)

F&F products are covered by an 24 months warranty from date of purchase

### PURPOSE

Staircase timer ASO-202 serves to keep switched-ON lighting of staircase, corridor, or any other object for the set time and to switch-OFF this lighting automatically, upon elapse of this set time.

### FUNCTIONING

Turned ON staircase timer supports the lighting during set time by potentiometer (from 0,5min. to 10min.). After passage of set time timer will switch OFF the lighting automatically. After switching OFF the lighting there is possibility to switch it ON again. Function of counter blockade does not allow to keep the light-ON in case of staircase switch blocking (after blocking the pushbutton, for example by match, the timer will count the set time and switch OFF the lighting). Next switching ON can be after removing the blockade.

### ATTENTION!

The ASO-202 is adapted to co-operate with pushbuttons equipped with neon lamp.


### ASSEMBLY

1. Fast the relay to substrate by 2 screws.
2. Take OFF the power.
3. Connect the relay to circuitry with wiring diagram.
4. By flat screwdriver set to switching threshold.

### TECHNICAL DATA

supply	230V AC
current load	<16A
switching OFF delay (to set)	0,5+10min
switching ON delay	<1sec
power consumption	0,56W
connection	screw terminals 2,5mm <sup>2</sup>
working temperature	-25+50°C
dimensions	50×67×26mm
fixing	2 screws to substrate

### WIRING DIAGRAM



A090405