



# LED Middle POWER

## 3030 Product Data Sheet

### *BSLxx Series*

Created Date : 12 / 24 / 2013

Revision : 2.0, 3/4/2014

## LED Middle POWER 3030BSLxx Series

### 1. Description

The LiteON 3030 Product series is a wide beam angle standard-dimension package, combining the lifetime and reliability advantages of Light Emitting Diodes with the brightness of conventional lighting. It gives you total design freedom and unmatched brightness, creating a new opportunities for solid state lighting to displace conventional lighting technologies.

#### 1.1 Features


- Package in 8mm tape on 7" diameter reels.
- Compatible with automatic placement equipment.
- Compatible with infrared and vapor phase reflow solder process.
- EIA STD package.
- I.C. compatible.
- Meet green product and Pb-free(According to RoHS)

#### 1.2 Available Part Numbers

Type	Part Number
Bread Pastries	LTW-3030BSL24
Packed Meat	LTW-3030BSL30
Fresh Meat	LTW-3030BSL35
Vegetable	LTW-3030BSL42

## LED Middle POWER 3030BSLxx Series

### 2. Package Dimensions



Part No.	Lens Color	Source Color
LTW-3030BSL24	Orange	InGaN Blue
LTW-3030BSL30		
LTW-3030BSL35		
LTW-3030BSL42		

#### Notes:

1. All dimensions are in millimeters.
2. Tolerance is  $\pm 0.2$  mm (.008") unless otherwise noted.

## LED Middle POWER 3030BSLxx Series

### 3. Absolute Maximum Ratings at Ta=25°C

Parameter	Symbol	Rating	Unit
Power Dissipation	P <sub>o</sub>	1400	mW
Continuous Forward Current	I <sub>F</sub>	200	mA
Pulse Forward Current	I <sub>FP</sub>	260	mA
Operating Temperature Range	T <sub>opr</sub>	-40 ~ +100	°C
Storage Temperature Range	T <sub>stg</sub>	-40 ~ +100	°C
Junction Temperature	T <sub>j</sub>	≤ 125	°C

#### Notes :

1. 1/10 duty cycle, Pulse width ≤ 100 μs.
2. Forbid to operating at reverse voltage condition for long.
3. It is recommended to follow de-rating curve to use maximum rating to ensure LED can operated normally.

## LED Middle POWER 3030BSLxx Series

### 4. Electro-Optical Characteristics

#### 4.1 Typical Performance

Parameter	Symbol	Values					Unit	Test Condition
			Bread Pastries	Packed Meat	Fresh Meat	Vegetable		
Type	-	-					-	
Chromaticity Coordinates	x	Typ.	0.479	0.383	0.386	0.380	-	I <sub>F</sub> = 150mA
	y	Typ.	0.407	0.296	0.334	0.380		
Luminous Flux <sup>1</sup>	Φ <sub>v</sub>	Min	68	68	73	84	lm	
		Typ.	78	78	84	97		
		Max.	92	92	96	110		
Optical Efficiency	η <sub>opt</sub>	Typ.	80	80	86	100	lm/W	
Color Rendering Index	CRI	Min.	90	80	90	90	-	
Viewing Angle	2θ <sub>1/2</sub>	Typ.	120				deg	
Forward Voltage	V <sub>F</sub>	Min	5.8				V	
		Typ.	6.5					
		Max.	6.8					
Thermal Resistance	R <sub>js</sub>	Typ.	12				°C/W	
ESD-Withstand Voltage	ESD	Min	5K				HBM	V

#### Notes


- Luminous flux is the total luminous flux output as measured with an integrating sphere.
- I<sub>v</sub> (flux) classification code is marked on each packing bag.
- The chromaticity coordinates (x, y) is derived from the 1931 CIE chromaticity diagram.
- Caution in ESD:
 

Static Electricity and surge damages the LED. It is recommended using a wrist band or anti-electrostatic glove when handling the LED. All devices, equipment and machinery must be properly grounded.
- CAS140B is the test standard for the chromaticity coordinates (x, y) & v.
- R<sub>9</sub> of fresh meat series is >60, and R<sub>10</sub> of bread pastries series is >80.
- The chromaticity coordinates (x, y) guarantee should be added +/- 0.01 tolerance
- CRI measurement allowance is ±5

## LED Middle POWER 3030BSLxx Series


### 4.2 Forward Current vs. Lumen and Voltage

Current (mA)	V <sub>F</sub> (V)	Lumen (lm)			
		Bread Pastries	Packed Meat	Fresh Meat	Vegetable
20	5.41	12.5	12.5	13.5	15.6
40	5.60	24.1	24.1	25.9	30.0
60	5.76	34.7	34.7	37.4	43.1
80	5.90	44.5	44.5	47.9	55.3
100	6.09	55.0	55.0	59.2	68.4
120	6.21	63.2	63.2	68.1	78.6
140	6.38	72.6	72.6	78.2	90.3
160	6.54	80.7	80.7	86.9	100.4
180	6.67	90.2	90.2	97.2	112.2
200	6.77	96.8	96.8	104.3	120.4




# LED Middle POWER 3030BSLxx Series

## 4.3 Relative Spectral Power Distribution at Typical Current




## 4.4 Radiation Characteristics




# LED Middle POWER 3030BSLxx Series


## 4.5 Forward Current vs. Forward Voltage



## 4.6 Forward Current Derating Curve vs. Ambient Temperature




## 4.7 Relative Intensity vs. Junction Temperature







# LED Middle POWER 3030BSLxx Series

## 4.8 Voltage vs. Junction Temperature





## 4.9 CIE X, Y vs. Current



# LED Middle POWER 3030BSLxx Series

## 4.10 CIE X, Y vs. Temperature



## LED Middle POWER 3030BSLxx Series


### 5. Binning Definition

#### 5.1 Color Bin

##### ■ Color Rank of Bread Pastries

Bread Pastries (BP), If=150mA			
Rank	-	x	y
<b>C1</b>	1	0.4748	0.4202
	2	0.4948	0.4228
	3	0.4834	0.3938
	4	0.463	0.3916
<b>Center</b>	5	0.4791	0.407

Tolerance on each Hue bin (x,y) is +/- 0.01.




# LED Middle POWER 3030BSLxx Series

■ Color Rank of Packed Meat

Packed Meat (PM), If=150mA			
Rank	-	x	y
E1	1	0.3806	0.3083
	2	0.3989	0.3103
	3	0.3852	0.2827
	4	0.3679	0.2809
Center	5	0.3829	0.2955

Tolerance on each Hue bin (x,y) is +/- 0.01.




# LED Middle POWER 3030BSLxx Series

■ Color Rank of Fresh Meat

Fresh Meat (FM), If=150mA			
Rank	-	x	y
F1	1	0.3829	0.3456
	2	0.4002	0.3496
	3	0.3885	0.3230
	4	0.3722	0.3192
Center	5	0.3857	0.3343


Tolerance on each Hue bin (x,y) is +/- 0.01.



## LED Middle POWER 3030BSLxx Series

■ Color Rank of Vegetable

Vegetable (VT), If=150mA			
Rank	-	x	y
<b>G1</b>	1	0.3750	0.3897
	2	0.3948	0.3997
	3	0.3851	0.3701
	4	0.3653	0.3603
<b>Center</b>	5	0.3800	0.3800



## LED Middle POWER 3030BSLxx Series

### 5.2 Flux Bin

<b>BP</b>	$\Phi_v$ Luminous Flux Spec. Table	
$\Phi_v$ Bin	Lumen (lm) at $I_F = 150$ mA	
	Min	Max
S1	68	78
S2	78	92

<b>FM</b>	$\Phi_v$ Luminous Flux Spec. Table	
$\Phi_v$ Bin	Lumen (lm) at $I_F = 150$ mA	
	Min	Max
S1	74	84
S2	84	96

<b>PM</b>	$\Phi_v$ Luminous Flux Spec. Table	
$\Phi_v$ Bin	Lumen (lm) at $I_F = 150$ mA	
	Min	Max
S1	68	78
S2	78	92

<b>VT</b>	$\Phi_v$ Luminous Flux Spec. Table	
$\Phi_v$ Bin	Lumen (lm) at $I_F = 150$ mA	
	Min	Max
S1	84	97
S2	97	110

Tolerance on each Luminous Flux bin is +/- 10%.

## LED Middle POWER 3030BSLxx Series

### 5.3 Voltage Bin

V <sub>F</sub> Spec. Table		
V <sub>F</sub> Bin	Forward Voltage (volts) at I <sub>F</sub> = 150mA	
	Min	Max
V1	5.8	6.0
V2	6.0	6.2
V3	6.2	6.4
V4	6.4	6.6
V5	6.6	6.8

Tolerance on each Forward Voltage bin is +/- 0.1V

### 6. Bin Code List

※ Notes: Full Rank on Label


Example: V1 / S1 / C1

Forward Voltage Rank	Luminous Flux Rank	Color Rank
V1	S1	C1



## LED Middle POWER 3030BSLxx Series

### 7. Reflow Soldering Characteristics



Profile Feature	Lead Free Assembly
Average Ramp-Up Rate (T <sub>Smax</sub> to T <sub>P</sub> )	3°C / second max
Preheat Temperature Min (T <sub>Smin</sub> )	150°C
Preheat Temperature Max (T <sub>Smax</sub> )	200°C
Preheat Time (t <sub>Smin</sub> to t <sub>Smax</sub> )	60 – 180 seconds
Time Maintained Above Temperature (T <sub>L</sub> )	217°C
Time Maintained Above Time (t <sub>L</sub> )	60 – 150 seconds
Peak / Classification Temperature (T <sub>P</sub> )	260°C
Time Within 5°C of Actual Peak Temperature (t <sub>p</sub> )	5 seconds
Ramp – Down Rate	6°C / second max
Time 25°C to Peak Temperature	8 minutes max

#### Notes:

- The LEDs can be soldered using the reflow soldering or hand soldering method. The recommended hand soldering condition is 350 °C max. and 2 secs max. for one time only, and the recommended reflow soldering condition is 260 °C max. and 5 secs max. for three times max.
- All temperatures refer to topside of the package, measured on the package body surface.

## LED Middle POWER 3030BSLxx Series

3. The soldering condition referring to J-STD-020B. The storage ambient for the LEDs should not exceed 30 °C temperature or 70% relative humidity. It is recommended that LEDs out of their original packaging are soldered within one week. For extended storage out of their original packaging, it is recommended that the LEDs were stored in a sealed container with appropriate desiccant, or desiccators with nitrogen ambient. If the LEDs were unpacked more than 168hrs, baking the LEDs at 60 °C for 60 mins before soldering process.
4. The soldering profile could be further referred to different soldering grease material characteristic. The grease vendor will provide this information.
5. A rapid-rate process is not recommended for the LEDs cooling down from the peak temperature.
6. Although the recommended reflow conditions are specified above, the reflow or hand soldering condition at the lowest possible temperature is desirable for the LEDs.
7. LiteOn cannot make a guarantee on the LEDs which have been already assembled using the dip soldering method.

## LED Middle POWER 3030BSLxx Series

### 8. Reliability Test

No	Test item	Test Condition	Duration	Number of Damaged
1	Steady State Operating Life of High Temperature (HTOL)	Ta=85°C, I <sub>F</sub> =150mA	1000 hrs	0/20
2	Steady State Operating Life of Low Temperature (LTOL)	Ta=-40°C, I <sub>F</sub> =150mA	1000 hrs	0/20
3	Pulse Wet Operating Life of High Temperature (PWHTOL)	60°C/90%RH, I <sub>F</sub> =150mA 30mins ON/30min OFF	500 hrs	0/20
4	High Temperature Storage (HTS)	100°C	1000 hrs	0/20
5	Low Temperature Storage (LTS)	-40°C	1000 hrs	0/20
6	Thermal Cycle (TC)	-40°C~100°C 30min dwell 5min transfer	200 cycles	0/20
7	Thermal Shock (TS)	-40°C~100°C 20min dwell 20sec transfer	200 cycles	0/20
8	Solder Resistance (SR)	265°C, 3X MSL	5sec	0/20
9	Solder Ability (SA)	245°C 5sec, 95% coverage	5sec	0/11
10	Mechanical Shock (MS)	1500G 0.5msec pulse shock	each 6 axis	0/6
11	Random Vibration (RV)	6G RMS, 10-2000Hz, 10min	per axis	0/6
12	Variable Vibration Frequency (VVF)	10-2000-10Hz, log or linear sweep rate, 20G for 1 min, 1.5mm each apply 3x per axis	over 6hrs	0/6
13	Salt Spread (SS)	35°C, 30g/m <sup>2</sup> /day	48hrs	0/11

Criteria for Judging the Damage

Item	Symbol	Test Condition	Criteria for Judgment	
			Min.	Max.
Forward Voltage	V <sub>F</sub>	I <sub>F</sub> =Typical Current		U.S.L. x 1.1
Luminous Flux	Im	I <sub>F</sub> =Typical Current	L.S.L. x 0.7	
CCX&CCY	x,y	I <sub>F</sub> =Typical Current		Shift<0.02


# LED Middle POWER 3030BSLxx Series

## 9. User Guide


### ■ Cleaning

Do not use unspecified chemical liquid to clean LED they could harm the package. If cleaning is necessary, immerse the LED in ethyl alcohol or isopropyl alcohol at normal temperature for less than one minute.

### ■ Recommend Printed Circuit Board Attachment Pad




### ■ Package Dimensions of Tape



**Note:** All dimensions are in millimeters (inches).

## LED Middle POWER 3030BSLxx Series

### ■ Package Dimensions of Reel



### Notes:

1. Empty component pockets sealed with top cover tape.
2. 7 inch reel-1000 pieces per reel.
3. Minimum packing quantity is 500 pieces for remainders.
4. The maximum number of consecutive missing lamps is two.
5. In accordance with EIA-481-1-B specifications.

## LED Middle POWER 3030BSLxx Series

### 10. Cautions

#### 10.1 Application

The LEDs described here are intended to be used for ordinary electronic equipment (such as office equipment, communication equipment and household applications). Consult Liteon's Sales in advance for information on applications in which exceptional reliability is required, particularly when the failure or malfunction of the LEDs may directly jeopardize life or health (such as in aviation, transportation, traffic control equipment, medical and life support systems and safety devices).

#### 10.2 Storage

This product is qualified as Moisture sensitive Level 3 per JEDEC J-STD-020 Precaution when handling this moisture sensitive product is important to ensure the reliability of the product.

The package is sealed:

The LEDs should be stored at 30°C or less and 90%RH or less. And the LEDs are limited to use within one year, while the LEDs is packed in moisture-proof package with the desiccants inside.

The package is opened:



The LEDs should be stored at 30°C or less and 60%RH or less. Moreover, the LEDs are limited to solder process within 72hrs. If the Humidity Indicator shows the pink color in 10% even higher or exceed the storage limiting time since opened, that we recommended to baking LEDs at 60°C at least 24hrs. To seal the remainder LEDs return to package, it's recommended to be with workable desiccants in original package.

#### 10.3 Cleaning

Use alcohol-based cleaning solvents such as isopropyl alcohol to clean the LED if necessary.

#### 10.4 Drive Mode

An LED is a current-operated device. In order to ensure intensity uniformity on multiple LEDs connected in parallel in an application, it is recommended that a current limiting resistor be incorporated in the drive circuit, in series with each LED as shown in Circuit A below



## LED Middle POWER 3030BSLxx Series

(A) Recommended circuit.

(B) The brightness of each LED might appear different due to the differences in the I-V characteristics of those LEDs.

### 10.5 ESD (Electrostatic Discharge)

Static Electricity or power surge will damage the LED. Suggestions to prevent ESD damage:

- Use of a conductive wrist band or anti-electrostatic glove when handling these LEDs.
- All devices, equipment, and machinery must be properly grounded.
- Work tables, storage racks, etc. should be properly grounded.
- Use ion blower to neutralize the static charge which might have built up on surface of the LED's plastic lens as a result of friction between LEDs during storage and handling.

ESD-damaged LEDs will exhibit abnormal characteristics such as high reverse leakage current, low forward voltage, or "no lightup" at low currents. To verify for ESD damage, check for "light up" and  $V_f$  of the suspect LEDs at low currents. The  $V_f$  of "good" LEDs should be  $>2.0V$  per die @0.1mA for InGaN product and  $>1.4V$  per die @0.1mA for AlInGaP product.

### 10.6 Suggested Checking List:

- Training and Certification
  1. Everyone working in a static-safe area is ESD-certified?
  2. Training records kept and re-certification dates monitored?
- Static-Safe Workstation & Work Areas
  1. Static-safe workstation or work-areas have ESD signs?
  2. All surfaces and objects at all static-safe workstation and within 1 ft measure less than 100V?
  3. All ionizer activated, positioned towards the units?
  4. Each work surface mats grounding is good?
- Personnel Grounding
  1. Every person (including visitors) handling ESD sensitive (ESDS) items wear wrist strap, heel strap or conductive shoes with conductive flooring?
  2. If conductive footwear used, conductive flooring also present where operator stand or walk?

## LED Middle POWER 3030BSLxx Series

3. Garments, hairs or anything closer than 1 ft to ESD items measure less than 100V\*?
4. Every wrist strap or heel strap/conductive shoes checked daily and result recorded for all DLs?
5. All wrist strap or heel strap checkers calibration up to date?

Note: \*50V for Blue LED.

- Device Handling
  1. Every ESDS items identified by EIA-471 labels on item or packaging?
  2. All ESDS items completely inside properly closed static-shielding containers when not at static-safe workstation?
  3. No static charge generators (e.g. plastics) inside shielding containers with ESDS items?
  4. All flexible conductive and dissipative package materials inspected before reuse or recycle?
- Others
  1. Audit result reported to entity ESD control coordinator?
  2. Corrective action from previous audits completed?
  3. Are audit records complete and on file?

### 10.7 Others:

- Do not put any pressure on the light emitting surface either by finger or any hand tool and do not stack the products. Stress or pressure may cause damage to the wires of the LED array.
- This product is not designed for the use under any of the following conditions, please confirm the performance and reliability are well enough if you use it under any of the following conditions
- Do not use sulfur-containing materials in commercial products including the materials such as seals and adhesives that may contain sulfur.
- Do not put this product in a place with a lot of moisture (over 85% relative humidity), dew condensation, briny air, and corrosive gas (Cl, H<sub>2</sub>S, NH<sub>3</sub>, SO<sub>2</sub>, NO<sub>x</sub>, etc.), exposure to a corrosive environment may affect silver plating.
- The appearance and specifications of the product may be modified for improvement without prior notice.