

RS5
PCB mounting

ROTARY SWITCHES UP TO 130mA 150VDC/AC
Optional actuator and PCB terminal



Feature

- 1 to 4 poles, 1 to 12 positions
- Three kinds of lever type
- Shorting or Non-shorting timing

Specification

- Load Rating: 130mA 150VDC/AC
- Contact Resistance: 25 mΩ Max (initial)
- Insulation Resistance: DC 500V 100MΩ Min.
- Dielectric Strength: 1000VAC 1 Minute
- Mechanical Life: 20000 cycles Min.
- Electrical Life: 15000 cycles Min.
- Operating Torque: 1kgf-cm (Max)

How to Order

RS5 — C — 12 — NS

Cap Style		Combination				Timing	
A		No.	Pole	Position	Stop	YS	Shorting
B		11	1	2	Yes	NS	Non-Shorting
C		12	1	12	Yes		
		13	1	12	No		
		21	2	2	Yes		
		22	2	6	Yes		
		23	2	6	No		
		31	3	2	Yes		
		32	3	4	Yes		
		33	3	4	No		
		41	4	2	Yes		
		42	4	3	Yes		
		43	4	3	No		
		61	6	2	Yes		
		63	6	2	No		

