Note: This datasheet may be out of date.
Please download the latest datasheet of BLM18PG300SN1# from the official website of Murata Manufacturing

https://www.murata.com/en-eu/products/productdetail?partno=BLM18PG300SN1%23

### BLM18PG300SN1#

"#" indicates a package specification code.








< List of part numbers with package codes >

BLM18PG300SN1J BLM18PG300SN1D BLM18PG300SN1B



### Appearance & Shape







- 1.The chip ferrite beads BLM series is designed to function nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
  BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.
- 2.The nickel barrier structure of the external electrodes provides excellent solder heat resistance.
- 3.BLM\_P series can be used in high current circuits due to its low DC resistance. It can match power lines to a maximum of 3ADC.

# A

### **Applications**

Other Usage For general



## **Packaging Information**

Packaging	Specifications	Minimum Order Quantity
J	330mm Paper Tape	10000
D	180mm Paper Tape	4000
В	Bulk(Bag)	1000

1 of 3

#### Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/05/20



Note: This datasheet may be out of date Please download the latest datasheet of BLM18PG300SN1# from the official website of Murata Manufacturing

Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM18PG300SN1%23

# BLM18PG300SN1#

"#" indicates a package specification code.



Shape	SMD
Size Code (in mm)	1608
Size Code (in inch)	0603
Length	1.6mm
Length Tolerance	±0.15mm
Width	0.8mm
Width Tolerance	±0.15mm
Thickness	0.8mm
Thickness Tolerance	±0.15mm
Impedance (at 100MHz)	30Ω
Impedance (at 100MHz) Tolerance	(Тур.)
Rated Current (at 85°C)	1A
Rated Current (at 125°C)	1A
DC Resistance(max.)	0.05Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.005g
Number of Circuit	1

2 of 3

#### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/05/20

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Note: This datasheet may be out of date.


Please download the latest datasheet of BLM18PG300SN1# from the official website of Murata Manufacturing


Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM18PG300SN1%23

# BLM18PG300SN1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

**Equivalent Circuit** 

3 of 3

#### Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/05/20

<sup>1.</sup> This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.