Note: This datasheet may be out of date

Please download the latest datasheet of BLM21BB750SN1# from the official website of Murata Manufacturing

https://www.murata.com/en-eu/products/productdetail?partno=BLM21BB750SN1%23

BLM21BB750SN1#

"#" indicates a package specification code.








< List of part numbers with package codes >

BLM21BB750SN1D BLM21BB750SN1J BLM21BB750SN1B



Appearance & Shape







The chip ferrite beads BLM series is designed to work nearly as a resistor at noise frequencies, which greatly reduces the possibility of resonance and leaves signal wave forms undistorted.
BLM series is effective in circuits without stable ground lines because BLM series does not need a connection to ground.

BLM_B series can minimize attenuation of the signal waveform due to its sharp impedance characteristics. Various impedances are available to match signal frequency.

The nickel barrier structure of the external electrodes provides excellent solder heat resistance.



Other Usage

For general



Packaging Information

Packaging	Specifications	Minimum Order Quantity
D	180mm Paper Tape	4000
J	330mm Paper Tape	10000
В	Bulk(Bag)	1000

1 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering.

2. This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/05/20

 $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM21BB750SN1\# \ from \ the \ of ficial \ website \ of \ Murata \ Manufacturing}$ Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM21BB750SN1%23

BLM21BB750SN1#

"#" indicates a package specification code.

Note: This datasheet may be out of date



Shape	SMD
Size Code (in mm)	2012
Size Code (in inch)	0805
Length	2.0mm
Length Tolerance	±0.2mm
Width	1.25mm
Width Tolerance	±0.2mm
Thickness	0.85mm
Thickness Tolerance	±0.2mm
Impedance (at 100MHz)	75Ω
Impedance (at 100MHz) Tolerance	±25%
Rated Current (at 85°C)	700mA
Rated Current (at 125°C)	700mA
DC Resistance(max.)	0.16Ω
Operating Temperature Range	-55°C to 125°C
Mass(typ.)	0.01g
Number of Circuit	1

2 of 3

Attention

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/05/20

^{1.} This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.


Note: This datasheet may be out of date. $\underline{ Please \ download \ the \ latest \ data sheet \ of \ BLM21BB750SN1\# \ from \ the \ of ficial \ website \ of \ Murata \ Manufacturing}$


Co., Ltd. https://www.murata.com/en-eu/products/productdetail?partno=BLM21BB750SN1%23

BLM21BB750SN1#

"#" indicates a package specification code.







Impedance-Frequency Characteristics

Equivalent Circuit

3 of 3

Attention

1. This datasheet is downloaded from the website of Murata Manufacturing Co., Ltd. Therefore, it's specifications are subject to change or our products in it may be discontinued without advance notice. Please check with our sales representatives or product engineers before ordering. 2.This datasheet has only typical specifications because there is no space for detailed specifications.

Therefore, please review our product specifications or consult the approval sheet for product specifications before ordering



URL: https://www.murata.com/

Last updated :2019/05/20