

LogiLink_®

Power Adapter
with PIR Motion Detector

Art. No.: PA0153


The energy saving Power Adapter with Motion sensor is perfect for garage, hallway, living room and watering appliances.

Features:

- » Automatically switch ON the power supply when human motion detected
- » 120° detection zone to sense movement up to 9m away
- » Automatically identify day and night with the LUX switch
- » Sensor's Sensitivity adjustable according to the location
- » Time-Delay is added continually: When it receives the second induction signals within the first induction, it will restart to time from the moment
- » Easy setup and energy saving
- » Perfect for dark rooms or hallways and works great with powered animal feeding and watering appliances







Automatically identify day and night

* The specifications and pictures are subject to change without notice.
*All trade names referenced are the registered namework of their respective owners.



Automatically turn ON when human motion detected













LogiLink_®

Power Adapter with PIR Motion Detector

Art. No.: PA0153

Specification:

Power Input	AC 220V~240V 50Hz, 6A max
Rated Load	Max.1200W (Light bulb) Max. 300W (LED)
Ambient Light	3~2000LUX (adjustable)
Detection Range	120°
Detection Distance	2~9m (<24°C) adjustable
Detection Moving Speed	0.6~1.5m/s
Time Delay	Min.10±3 seconds Max. 7±2 minutes
Power Consumption	Approx. 0.5W
Operating Temperature	-20°C~40°C
Operating Humidity	<93%RH











Package Contents:

- » 1 x Power Adapter
- » 1 x User Manual

Package Informations:

- » Packing Dimension:
- » Packing Weight: kg
- » Carton Dimension: mm
- » Carton Q'ty: pcs
- » Carton Weight: kg

Warning

- *Only to be used indoor.
- *Only to be used after powering on.
- *Only to be used within max load.















